TEHNIČKA DOKUMENTACIJA

Za revitalizaciju spoljne rasvjete u VN postrojenju

TS 110/35 kV – ULCINJ

OPIS RADOVA: Revitalizacija sistema spoljašnje rasvjete VN postrojenja

OBJEKAT: Trafostanica 110/35 kV, ULCINJ

LOKACIJA: Ulcinj, Crna Gora

INVESTITOR: Crnogorski elektroprenosni sistem AD, Podgorica

1. PREDMET PROJEKTA:

Za potrebe Investitora (CGES-a), potrebno je izvršiti kompletnu revitalizaciju sistema osvetljenja spoljne rasvjete (SR) trafostanice 110/35kV Ulcinj. Novo rješenje je potrebno izvesti sa novijim energetski efikasnijim LED svetiljkama, uz obezbjeđivanje boljih uslova osvijetljenosti u odnosu na postojeće stanje. Obzirom na dotrajalost i stanje postojećih instalacija, predviđa se kompletna zamjena svih djelova sistema spoljne rasvjete novim. To obuhvata demontažu svih postojećih stubova rasvjete u postrojenju, zatim nabavku, transport i ugradnju novih elemenata tj. svjetiljki, pod-konstrukciju za iste, kablova za napajanje ormana i svjetiljki kao i ormane za razvod i upravljanje rasvjetom. Nove instalacije je potrebno izvesti u svemu prema usvojenom fotometrijskim rješenju, grafičkim prilozima kao i uz poštovanje svih zakonodavnih propisa i pozitivne inženjerske prakse.

2. CILJ PROJEKTA:

Revitalizacijom postojećeg sistema spoljašnje rasvjete planirano je unapređenje osvijetljenosti VN postrojenja u cilju zadovoljenja standarda, povećanje energetske efikasnosti i smanjenje emisije CO2, smanjenje troškova održavanja, kao i povećanje bezbjednosti kretanja i obavljanja radnih zadataka kroz VN postrojenje u noćnim satima. Novo rješenje mora biti u skladu sa aktuelnim standardom MEST EN 12464-2:2014, a konačan cilj projekta jeste funkcionalna rasvjeta kompletnog područja trafostanice.

3. LOKACIJA

Predmenta lokacija se nalazi na katastarskoj parceli br. 4880, KO Ulcinj, Opština Ulcinj, pozicionirana na kraju saobraćajnice u okolnom naselju, gdje je i saobraćajni pristup. Lokacija je na relativno ravnom terenu sa uzdignutim terenom po obodu, pravilnog oblika na kojoj se nalazi postrojenje 110 kV, komandna zgrada sa pomoćnim objektima. Površina parcele je ≈ 4.100 m^2.

4. OPIS POSTOJEĆEG STANJA

Obzirom na starost i dotrajalost postojeće instalacije spoljne rasvjete, predviđena je demontaža postojećih stubova u postrojenju (stubovi visine 4m). Obzirom da su stubovi zaliveni u betonskom temelju, iste je potrebno isjeći u dnu zatim rupe u temelju je potrebno zatvoriti kombinovanjem pur-pjene i adekvatnog silikona kako bi se spriječio ulazak vode u iste. Postojeće kablove u postrojenju nije potrebno demontirati.

5. PROJEKTOVANI RADOVI

5.1 RASVJETA I PRORAČUN

Projektom je predviđena implementacija novog sistema rasvjete sa novim LED svjetiljkama koje posjeduju dodatnu zaštitu od prenapona, u broju i pozicijama potrebnim za zadovoljenje nivoa osvjetljaja prema standardu MEST EN 12464-2:2014. Po ovom standardu, u tabeli 5.11 za elektrane I postrojenja, za "Overall Inspection" zahtjeva se srednji osvjetljaj od 50lx I ravnomjernost 0.4. Ovaj standard je potrebno zadovoljiti u zonama razvodnih postrojenja (RP) 110kV, sabirničkih sistema, kao i energetskih transformatora (ETR). Pored gore popisanih postrojenja, na predmetnoj lokaciji postoje još nekoliko različitih zona/prostora koje je potrebno osvijetliti u sledećim nivoima osvijetljenosti i ravnomjernosti:

ZONA 1 (niži nivo)

- Ulazna kapija – srednja osvijetljenost >50lx / ravnomjernost >0.5.
- Ulazni, Centralni i Sporedni koridor – srednja osvijetljenost >15lx / ravnomjernost >0.5.
- Koridor RP 110kV – srednja osvijetljenost >30lx / ravnomjernost >0.4.
- Postrojenja 110kV i ETR – srednja osvijetljenost >25lx / ravnomjernost >0.4.
- Perimetri (zone uz ograde) – srednja osvijetljenost >5lx / ravnomjernost >0.5.

ZONA 2 (viši nivo)

- Ulazna kapija – srednja osvijetljenost >50lx / ravnomjernost >0.5.
- Ulazni, Centralni i Sporedni koridor – srednja osvijetljenost >15lx / ravnomjernost >0.5.
- Koridor RP 110kV – srednja osvijetljenost >40lx / ravnomjernost >0.4.
- Postrojenja 110kV i ETR – srednja osvijetljenost >50lx / ravnomjernost >0.6.
- Perimetri (zone uz ograde) – srednja osvijetljenost >7.5lx / ravnomjernost >0.4.

DEA (nezavisna rasvjeta)

Uz rasvjetu postrojenja potrebno je osvijetliti i prostor oko DEA, koji će se nezavisno paliti sa grebenastog prekidača na KO u komandnoj sobi. Zbog rasporeda opreme, broj i raspored svjetiljki je fiksan. Potreban nivo osvjetljaja je:

- srednja osvijetljenost >200lx / ravnomjernost >0.6

Osim zamjene svetiljki projekat obuhvata i promjenu načina regulacije i upravljanja svetiljki sa ciljem racionalizacije potrošnje električne energije kao i samog intervala rada svetiljki (u dva nivoa – dva paljenja tj. dvije zone). Zona 1, definiše opšti nivo za cirkulaciju postrojenjem, dok zona 2 definiše maksimalni nivo, kojim se ispunjava gore opisani standard. Regulacija ova dva nivoa rasvjete se obavlja u komandnom ormanu (KO) koji je predviđen za montažu u komandnoj sobi, pomoću grebenastih prekidača (1-0-2 za zonu 1 i 1-0 za zonu 2) sa kog se komanduje i rasvjetom DEA.

Fotometrijskim proračunom je potrebno zadovoljiti tražene vrijednosti za obije zone upravljanja rasvjetom, te iste prikazati kao posebne scene u proračunu. Prilikom izvođenja, izvođač treba da poštuje sve pozitivne zakonske propise i prakse i da u skladu sa istima vrši radove, bez obzira da li su isti navedeni ili nisu u ovom projektu. Na podlogama za fotometrijski proračun dati su kompletni detalji potrebni za izradu proračuna, sa svim ucrtanim elementima, njihovim dimenzijama i uputima za njihovo formiranje u samom proračunu. Elemente date na podlozi je obavezno tretirati u proračunu.

U cilju provjere ispravnosti fotometrijskog proračuna, Izvođač je dužan dostaviti fotometrijski fajl (.evo npr) kako bi Investitor mogao provjeriti sve elemente proračuna.

5.2 KABLOVSKA INSTALACIJA I RAZVODNI ORMANI

Projektom je previđeno komplet polaganje novog napojnog kabla, na relaciji od ormana NN razvoda (odakle se napaja sistem spoljne rasvjete) do ormana GOSR (glavni orman spoljne rasvjete), zatim svi kablovi na relaciji od GOSR do lokalnih ormana na portalima postrojenja i lokalnih svjetiljki na fasadi objekta.

GOSR je predviđen kao nadgradni, na zidu u prostoriji iza komandne sobe u kom se nalazi i NN razvod sa kog se napaja. Za isti je predviđeno napajanje sa postojećeg ormana NN razvoda, gdje je potrebno izraditi priključak sa postojećih sabirnica ormana. U istom je potrebno smjestiti i prekidačku/osiguračku opremu „drišer" za zaštiti glavnog napojnog kabla ka GOSR. Napojni kabl do GOSR je tipa **NYCY 4x6mm2**, kojeg štite nožasti osigurač NH01C 25A. Kabl se polaže kroz postojeće betonske kablovske kanale u podu, a dio od kablovskog kanala do ormana GOSR po zidu se polaže u PNK regalu 100mm.

Sa GOSR se napajaju svi lokalni ormani rasvjete (RO-A i B), kablovima tipa NYCY **4x4mm2**. Kablovi se polažu kroz postojeće betonske kanale i cijevi, do krajnjih tačaka postojećih kanala blizu stubova, zatim dijelom kroz energetska crijeva u zemljanom rovu do samih stubova, gdje se polažu nadgradno u PNK regalima 50mm po betonskom temelju i uz stub do pripadajućih ormana. Sa GOSR se još napajaju svjetiljke i foto-ćelija na fasadi objekta, kablovima tipa NYCY **3x1.5mm2**. Ovi kablovi se dijelom polažu kroz postojeće betonske kanale i cijevi u objektu, zatim unutrašnjim zidovima objekta nadgradno u HF

cijevima ili PNK 100mm do izlaza iz objekta. Zatim se fasadom polažu u PVC kanalicama odgovarajućih dimenzija, u zavisnosti od količine kablova koji se u njima polažu.

Sa lokalnih ormana rasvjete u polju (RO - A i B) se napajaju svjetiljke na portalima, kablovima tipa **NYCY 3x1.5mm2**. Kablovi se od pripadajućeg RO vodi do svake svjetiljke, nadgradno po metalnoj konstrukciji stuba kroz pripadajuće **SAPA** crijevo, pričvršćujući se na svakih 1m za istu. Dio trase gdje ovi kablovi idu kroz zemlju, vode se u energetska crijeva, kako je to predviđeno grafičkim prilozima i specifikacijom radova.

Komanda (paljenje) rasvjete je predviđeno putem dva grebenasta prekidača koji će biti montirani na malom ormanu KO u komandnoj sobi komandne zgrade. Zona 1 kao osnovni scenario će se paliti preko preklopke „1-0-2" koja omogućava ručno paljenje (položaj 1) i automatski rad preko foto-ćelije (položaj 2). Zona 2 kao maksimalni scenario će se paliti pomoću preklopke „1-0". Pored ova dva grebenasta prekidača, na vratimo KO je predviđeno još jedan grebenasti prekidač „1-0" za paljenje rasvjete DEA prostora. U tu svrhu od GOSR do pozicije ormana KO se polaže kablovi tipa **NYCY 5x1.5mm2 (za zone 1 i 2) i NYCY 3x1.5mm^2 (za DEA).** Ovi kablovi se polažu dijelom nadgradno po unutrašnjim zidovima objekta u HF cijevima, a dijelom duplim podom do pozicije KO u komandnoj sobi.

Ormani na portalima za rasvjetu u polju (RO-A i B) moraju biti nadgradni, predviđeni za montažu na metalnu konstrukciju stubova. Ormani moraju biti izrađeni od poliestera ojačanog staklenim vlaknima otporan na UV zračenja i atmosferske uticaje, u zaštiti IP55.

Zbog blizine transformatora i relativno kratkih dionica kablova u energetskom smislu, sva sklopna tehnika korištena u ormanima mora biti isklopne moći 15kA.

5.3 POD-KONSTRUKCIJA I MONTAŽNO/DEMONTAŽNI RADOVI

Ovim projektom se ne tretiraju postojeći napojni kablovi za rasvjetu, već se oni zanemaruju. Postojeći stubovi za dekorativnu rasvjetu se demontiraju u skladu sa uputima na grafičkim prilozima i specifikaciji. Za svjetiljke koje se montiraju na portalima u 110kV postrojenju obavezna je izrada pod-konstrukcije (nosača) koji mora imati gumenu barijeru na mjestu montaže svjetiljke radi galvanskog odvajanja same svjetiljke od metalne mase stuba. Nosač je dovoljnog kapaciteta da "nosi" težinu svjetiljke i da istu drži u fiksnom položaju. Nosač je izrađen od čelika, sa adekvatnim premazima i antikorozivnom zaštitom i isti se mora bezbjedno povezati sa čeličnom konstrukcijom na koju se kači putem zavarivanja, šrafljenja ili ukliještanja. Postojeća konstrukcija na koju se kači nosač, mora biti adekvatno sanirana u slučaju oštećenja tokom radova. Tačan izgled i dimenzije pojedinačnih nosača uskladiti sa situacijom na licu mjesta i usvojenim fotometrijskim rješenjem.

5.4 ZAVRŠNE ODREDBE

Nakon svih izvedenih radova, Izvođač je dužan da izvrši testiranje i puštanje u rad spoljne rasvjete u prisustvu predstavnika Investitora. Po puštanju u rad, neophodno je izvršiti mjerenje nivoa osvjetljaja u skladu sa tačkama iz fotometrijskog proračuna. Devijacije u odnosu na proračunske vrijednosti ne smiju biti veće od 10%.

6. PRILOZI

6.1 NUMERIČKA DOKUMENTACIJA

Bilans snaga i energije – Spoljna rasvjeta TS UL
Proračun napojnih kablova – Spoljna rasvjeta TS UL
Fotometrijski proračun: Rasvjeta spoljašnjeg postrojenja TS UL

6.2 GRAFIČKA DOKUMENTACIJA

Prilog 1 – Situacija: Osnova trafostanice	R = 1:100
Prilog 2 – Situacija: Razvod kablova u postrojenju	R = 1:100
Prilog 3 – Objekat TS: Rasvjeta na fasadi objekata	R = 1:100
Prilog 4 – Postrojenje 110kV: Rasvjeta na portalima SS (RO-A)	R = 1:50
Prilog 5 – Postrojenje 110kV: Rasvjeta na portalima SS (RO-A)	R = 1:50
Prilog 6 – Postrojenje 110kV: Rasvjeta na 110kV portalima (RO-B)	R = 1:50
Prilog 7 – Objekat TS: Rasvjeta DEA	R = 1:50
Prilog 8 – Jednopolna šema ormana GOSR	
Prilog 9 – Jednopolna šema ormana RO-A	
Prilog 10 – Jednopolna šema ormana RO-B	
Prilog 11 – Jednopolna šema ormana KO	
Prilog 12 – Blok šema napajanja SR	
Prilog 13 – Legenda opreme	
Prilog 14 – Situacija: Podloga za fotometrijski proračun	R = 1:100

BILANS SNAGA				
Tip potrošača	Razvodni orman - Potrošač	Instal. Snaga (W)	Koef. jednovr.	Jedn. snaga (W)
GOSR	RO - A	377	1.00	377
	RO - B	377	1.00	377
	FASADA	498	1.00	498
Ukupna instalisana snaga (W)				1,252
Koeficijent jednovremenosti (K)				1.00
Ukupna jednovremena snaga (W)				**1,252**
Ukupna aktivna snaga P (W)				1,252
cos φ				0.95
Ukupna prividna snaga S (VA)				**1,318**
Potrebna godišnja energija (kWh)				**4,249**

Podgorica, Mart 2025.

Pripremio:

Blažo Janković, dipl. ing. el.

TABELA 1.

PRORAČUN NAPOJNIH KABLOVA

Relacija		Instal. Snaga	Koef. Jednov.	Jedn. Snaga	Fakt. snage	Struja	Tip i presjek kabla	Nosiv. kabla	"A"	Korekcioni faktori			"B"	"C"	"D"	"E"			Duž. kabla	Pad napona	
																				dionica	ukupno
od	do	P_i (W)	k_j	P_j (W)	cos φ	I_b (A)	(mm^2)	I_d(A)	/	K_n	K_θ	K_λ	I_z(A)	I_n(A)	/	I_2 (A)	1,45xI_z	/	l(m)	%	%
NN	GOSR	1,252	1.00	1,252	0.95	**1.90**	NYCY 4x6	**52**	C	0.80	1.00	1.00	**41.60**	25	1.60	40.00	60.32	**zadov.**	**18**	**0.042**	**0.042**
GOSR	RO-A	377	1.00	377	0.95	**0.57**	NYCY 4x4	**40**	C	0.70	0.80	1.00	**22.40**	20	1.35	27.00	32.48	**zadov.**	**93**	0.098	**0.140**
GOSR	RO-B	377	1.00	377	0.95	**0.57**	NYCY 4x4	**40**	C	0.70	0.80	1.00	**22.40**	20	1.35	27.00	32.48	**zadov.**	**104**	0.109	**0.151**
RO-B	B9	44	1.00	44	0.95	**0.20**	NYCY 3x1.5	**23**	E	0.70	0.80	1.00	**12.88**	10	1.35	13.50	18.68	**zadov.**	**38**	0.075	**0.227**

"A" - tip električnog razvoda: prema JUS N.B2. 752

"B" - trajno dozvoljena struja $I_z = In \times K_n \times K_\theta \times K_\lambda$ (A)

"C" - I_n - nazivna struja zaštitnog uredjaja - osiguraca (A).

"D" - koeficijent zaštitnog uredjaja - osiguraca (k)

"E" - $I_2 = I_n \times k$ - struja kod koje zaštitni uređaj pouzdano djeluje (A)

1. $I_b < I_n < I_z$
2. $I_2 < 1.45 \times I_z$

K_n - zbog paralelnog vodjenja kablova

K_θ - zbog temperature ambijenta

K_λ - zbog termičke otpornosti zemlje


Pripremio:

Blažo Janković, dipl. ing. el.

Podgorica, Mart 2025.

Date 11/03/2025

CRNOGORSKI ELEKTROPRENOSNI SISTEM AD



RASVJETA SPOLJAŠNJEG POSTROJENJA - TS ULCINJ

Created with DIALux

CRNOGORSKI ELEKTROPRENOSNI SISTEM AD

Table of Contents

Cover 1
Table of Contents 2
Description 4
Images 5

Product data sheets

LUG Light Factory - ATLANTYK 2.0 BASIC LED ED 2900m/840 PC opal IP65 grafit RAL7024 (1x LED 4000K) 17
LUG Light Factory - POWERLUG MINI LED ED 3600lm/740 IP65 as szeroki szary (1x LED 4000K) 18
LUG Light Factory - POWERLUG MINI LED ED 6000lm/740 IP65 as szeroki szary (1x LED 4000K) 19
LUG Light Factory - POWERLUG MINI LED ED 6300lm/740 IP65 as w¹ski szary (1x LED 4000K) 20
LUG Light Factory - POWERLUG MINI LED ED 6350lm/740 IP65 25st. szary (1x LED 4000K) 21


Site 1

Luminaire layout plan 22
Luminaire list 26
Calculation objects / SCENA 1 - ZONA 2 (FULL) 27
Calculation objects / SCENA 2 - ZONA 1 (LOW) 30
CS 1 - RP 110kV / SCENA 1 - ZONA 2 (FULL) / Perpendicular illuminance 33
CS 2 - RP 110kV / SCENA 1 - ZONA 2 (FULL) / Perpendicular illuminance 34
CS 3 - RP 110kV / SCENA 1 - ZONA 2 (FULL) / Perpendicular illuminance 35
CS 4 - ETR 2 / SCENA 1 - ZONA 2 (FULL) / Perpendicular illuminance 36
CS 5 - ETR 1 / SCENA 1 - ZONA 2 (FULL) / Perpendicular illuminance 37
CS 6 - Koridor RP / SCENA 1 - ZONA 2 (FULL) / Perpendicular illuminance 38
CS 7 - Ulaz (kapija) / SCENA 1 - ZONA 2 (FULL) / Perpendicular illuminance 39
CS 8 - Ulazni koridor / SCENA 1 - ZONA 2 (FULL) / Perpendicular illuminance 40
CS 9 - Centralni koridor / SCENA 1 - ZONA 2 (FULL) / Perpendicular illuminance 41
CS 10 - Sporedni koridor / SCENA 1 - ZONA 2 (FULL) / Perpendicular illuminance 42
CS 11 - Perimetar 1 / SCENA 1 - ZONA 2 (FULL) / Perpendicular illuminance 43
CS 12 - Perimetar 2 / SCENA 1 - ZONA 2 (FULL) / Perpendicular illuminance 44
CS 13 - DEA / SCENA 1 - ZONA 2 (FULL) / Perpendicular illuminance 45
CS 1 - RP 110kV / SCENA 2 - ZONA 1 (LOW) / Perpendicular illuminance 46
CS 2 - RP 110kV / SCENA 2 - ZONA 1 (LOW) / Perpendicular illuminance 47
CS 3 - RP 110kV / SCENA 2 - ZONA 1 (LOW) / Perpendicular illuminance 48
CS 4 - ETR 2 / SCENA 2 - ZONA 1 (LOW) / Perpendicular illuminance 49
CS 5 - ETR 1 / SCENA 2 - ZONA 1 (LOW) / Perpendicular illuminance 50
CS 6 - Koridor RP / SCENA 2 - ZONA 1 (LOW) / Perpendicular illuminance 51
CS 7 - Ulaz (kapija) / SCENA 2 - ZONA 1 (LOW) / Perpendicular illuminance 52
CS 8 - Ulazni koridor / SCENA 2 - ZONA 1 (LOW) / Perpendicular illuminance 53
CS 9 - Centralni koridor / SCENA 2 - ZONA 1 (LOW) / Perpendicular illuminance 54

CRNOGORSKI ELEKTROPRENOSNI SISTEM AD

Table of Contents

CS 10 - Sporedni koridor / SCENA 2 - ZONA 1 (LOW) / Perpendicular illuminance 55
CS 11 - Perimetar 1 / SCENA 2 - ZONA 1 (LOW) / Perpendicular illuminance 56
CS 12 - Perimetar 2 / SCENA 2 - ZONA 1 (LOW) / Perpendicular illuminance 57
CS 13 - DEA / SCENA 2 - ZONA 1 (LOW) / Perpendicular illuminance 58
Control groups 59



Description

RASVJETA SPOLJAŠNJEG POSTROJENJA - TS ULCINJ


Glavni inženjer SGUTA
Blažo Janković

CGES AD Podgorica
Bul.Sv. Petra Cetinjskog 18

T +382 69 010 553
F +382 20 416 836
blazo.jankovic@cges.me

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.


Images



Site 1 (145)

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.


Images



Site 1 (146)

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.


Images



Site 1 (147)

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.


Images



Site 1 (148)

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.


Images



Site 1 (149)

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.


Images



Site 1 (150)

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.


Images



Site 1 (151)

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.


Images



Site 1 (152)

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.


Images



Site 1 (153)

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.


Images



Site 1 (154)

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.


Images



Site 1 (155)

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Images




Site 1 (156)

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Product data sheet

LUG Light Factory - ATLANTYK 2.0 BASIC LED ED 2900m/840 PC opal IP65 grafit RAL7024

Article No.	090380.5L10.021
P	18.0 W
Φ_{Lamp}	2900 lm
$\Phi_{Luminaire}$	2900 lm
η	100.00 %
Luminous efficacy	161.1 lm/W
CCT	4000 K
CRI	80




Polar LDC

Product data sheet

LUG Light Factory - POWERLUG MINI LED ED 3600lm/740 IP65 as szeroki szary

Article No.	120212.5L171.41
P	25.0 W
Φ_{Lamp}	3600 lm
$\Phi_{Luminaire}$	3600 lm
η	100.00 %
Luminous efficacy	144.0 lm/W
CCT	4000 K
CRI	70




Polar LDC

Product data sheet

LUG Light Factory - POWERLUG MINI LED ED 6000lm/740 IP65 as szeroki szary

Article No.	120212.5L181.41
P	44.0 W
Φ_{Lamp}	6000 lm
$\Phi_{Luminaire}$	6000 lm
η	100.00 %
Luminous efficacy	136.4 lm/W
CCT	4000 K
CRI	70




Polar LDC

Product data sheet

LUG Light Factory - POWERLUG MINI LED ED 6300lm/740 IP65 as w[1]ski szary

Article No.	120212.5L181.31
P	44.0 W
Φ_{Lamp}	6300 lm
$\Phi_{Luminaire}$	6300 lm
η	100.00 %
Luminous efficacy	143.2 lm/W
CCT	4000 K
CRI	70




Polar LDC


Product data sheet

LUG Light Factory - POWERLUG MINI LED ED 6350lm/740 IP65 25st. szary

Article No.	120212.5L181.11
P	44.0 W
Φ_{Lamp}	6350 lm
$\Phi_{Luminaire}$	6350 lm
η	100.00 %
Luminous efficacy	144.3 lm/W
CCT	4000 K
CRI	70



Polar LDC




Cone diagram

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1

Luminaire layout plan



The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1

Luminaire layout plan

LUG Light Factory - 090380.5L10.021 - ATLANTYK 2.0 BASIC LED ED 2900m/840 PC opal IP65 grafit RAL7024
1x LED 4000K

X	Y	Mounting height	Housing rotation	MF	Luminaire
67.787 m	27.581 m	2.300 m	0.0° / -0.0° / 90.0°	0.90	27
66.488 m	25.807 m	2.300 m	0.0° / -0.0° / -0.0°	0.90	28
69.115 m	25.807 m	2.300 m	0.0° / -0.0° / -0.0°	0.90	29
67.787 m	24.019 m	2.300 m	0.0° / -0.0° / 90.0°	0.90	31

LUG Light Factory - 120212.5L171.41 - POWERLUG MINI LED ED 3600lm/740 IP65 as szeroki szary
1x LED 4000K

X	Y	Mounting height	Housing rotation	MF	Luminaire
29.287 m	51.706 m	6.700 m	0.0° / -0.0° / 90.0°	0.90	1
51.300 m	51.283 m	9.200 m	0.0° / -0.0° / 90.0°	0.90	2
62.100 m	51.283 m	9.200 m	0.0° / -0.0° / 90.0°	0.90	3
62.507 m	43.800 m	9.200 m	0.0° / -0.0° / -0.0°	0.90	10
46.115 m	43.219 m	5.000 m	-0.0° / -10.0° / 65.0°	0.90	11
46.115 m	42.474 m	5.000 m	0.0° / -10.0° / -65.0°	0.90	12
7.100 m	42.162 m	9.700 m	0.0° / -0.0° / -180.0°	0.90	14
62.507 m	29.350 m	9.200 m	0.0° / -0.0° / -0.0°	0.90	26
50.983 m	25.771 m	9.200 m	0.0° / -10.0° / -180.0°	0.90	30
68.221 m	16.407 m	7.800 m	0.0° / -0.0° / -0.0°	0.90	32
53.800 m	10.081 m	7.800 m	0.0° / -10.0° / -90.0°	0.90	34
62.900 m	10.081 m	7.800 m	0.0° / -10.0° / -90.0°	0.90	35

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1

Luminaire layout plan

LUG Light Factory - 120212.5L181.11 - POWERLUG MINI LED ED 6350lm/740 IP65 25st. szary
1x LED 4000K

X	Y	Mounting height	Housing rotation	MF	Luminaire
29.609 m	50.655 m	6.700 m	-0.0° / -55.0° / -20.0°	0.90	6
29.609 m	42.007 m	6.700 m	0.0° / -55.0° / -0.0°	0.90	16
29.609 m	33.400 m	6.700 m	-0.0° / -55.0° / 15.0°	0.90	21
68.036 m	10.081 m	7.800 m	0.0° / -45.0° / -50.0°	0.90	36

LUG Light Factory - 120212.5L181.31 - POWERLUG MINI LED ED 6300lm/740 IP65 as w[1]ski szary
1x LED 4000K

X	Y	Mounting height	Housing rotation	MF	Luminaire
20.359 m	50.326 m	6.700 m	-0.0° / -20.0° / -70.0°	0.90	7
29.232 m	50.326 m	6.700 m	0.0° / -20.0° / -110.0°	0.90	8
20.392 m	33.700 m	6.700 m	-0.0° / -20.0° / 70.0°	0.90	19
29.183 m	33.700 m	6.700 m	0.0° / -20.0° / 110.0°	0.90	20
7.300 m	32.664 m	9.700 m	0.0° / -25.0° / -90.0°	0.90	24
20.312 m	32.322 m	6.700 m	-0.0° / -25.0° / -90.0°	0.90	25
53.342 m	12.500 m	7.800 m	0.0° / -25.0° / -180.0°	0.90	33

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1

Luminaire layout plan

LUG Light Factory - 120212.5L181.41 - POWERLUG MINI LED ED 6000lm/740 IP65 as szeroki szary 1x LED 4000K

X	Y	Mounting height	Housing rotation	MF	Luminaire
8.472 m	50.888 m	9.700 m	0.0° / -0.0° / -0.0°	0.90	4
7.787 m	50.658 m	9.700 m	0.0° / -0.0° / -90.0°	0.90	5
50.951 m	48.707 m	9.200 m	0.0° / -0.0° / -180.0°	0.90	9
7.787 m	42.400 m	9.700 m	-0.0° / -10.0° / 90.0°	0.90	13
8.472 m	42.161 m	9.700 m	0.0° / -0.0° / -0.0°	0.90	15
7.787 m	41.638 m	9.700 m	0.0° / -10.0° / -90.0°	0.90	17
50.953 m	36.907 m	9.200 m	0.0° / -0.0° / -180.0°	0.90	18
7.787 m	33.400 m	9.700 m	0.0° / -0.0° / 90.0°	0.90	22
8.472 m	33.007 m	9.700 m	0.0° / -0.0° / -0.0°	0.90	23

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1

Luminaire list


Φ_{total}	P_{total}	Luminous efficacy
178300 lm	1252.0 W	142.4 lm/W


pcs.	Manufacturer	Article No.	Article name	P	Φ	Luminous efficacy
4	LUG Light Factory	090380.5L 10.021	ATLANTYK 2.0 BASIC LED ED 2900m/840 PC opal IP65 grafit RAL7024	18.0 W	2900 lm	161.1 lm/W
12	LUG Light Factory	120212.5L 171.41	POWERLUG MINI LED ED 3600lm/740 IP65 as szeroki szary	25.0 W	3600 lm	144.0 lm/W
4	LUG Light Factory	120212.5L 181.11	POWERLUG MINI LED ED 6350lm/740 IP65 25st. szary	44.0 W	6350 lm	144.3 lm/W
7	LUG Light Factory	120212.5L 181.31	POWERLUG MINI LED ED 6300lm/740 IP65 as w¹ski szary	44.0 W	6300 lm	143.2 lm/W
9	LUG Light Factory	120212.5L 181.41	POWERLUG MINI LED ED 6000lm/740 IP65 as szeroki szary	44.0 W	6000 lm	136.4 lm/W

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 1 - ZONA 2 (FULL))

Calculation objects





The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 1 - ZONA 2 (FULL))

Calculation objects

Calculation surfaces

Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 1 - RP 110kV Perpendicular illuminance Height: 0.020 m	69.4 lx	45.0 lx	78.8 lx	0.65	0.57	CG1
CS 2 - RP 110kV Perpendicular illuminance Height: 0.020 m	80.6 lx	52.4 lx	97.4 lx	0.65	0.54	CG2
CS 3 - RP 110kV Perpendicular illuminance Height: 0.020 m	70.4 lx	42.8 lx	93.6 lx	0.61	0.46	CG3
CS 4 - ETR 2 Perpendicular illuminance Height: 0.020 m	51.6 lx	41.2 lx	70.1 lx	0.80	0.59	CG4
CS 5 - ETR 1 Perpendicular illuminance Height: 0.020 m	52.6 lx	35.9 lx	71.3 lx	0.68	0.50	CG5
CS 6 - Koridor RP Perpendicular illuminance Height: 0.020 m	48.6 lx	20.0 lx	78.2 lx	0.41	0.26	CG6
CS 7 - Ulaz (kapija) Perpendicular illuminance Height: 0.020 m	54.2 lx	31.1 lx	77.9 lx	0.57	0.40	CG7
CS 8 - Ulazni koridor Perpendicular illuminance Height: 0.020 m	17.7 lx	9.21 lx	32.4 lx	0.52	0.28	CG8
CS 9 - Centralni koridor Perpendicular illuminance Height: 0.020 m	54.6 lx	33.8 lx	75.0 lx	0.62	0.45	CG9
CS 10 - Sporedni koridor Perpendicular illuminance Height: 0.020 m	19.3 lx	11.0 lx	37.2 lx	0.57	0.30	CG10
CS 11 - Perimetar 1 Perpendicular illuminance Height: 0.020 m	17.6 lx	9.81 lx	50.8 lx	0.56	0.19	CG11

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 1 - ZONA 2 (FULL))

Calculation objects


CS 12 - Perimetar 2 Perpendicular illuminance Height: 0.020 m	9.10 lx	4.32 lx	33.6 lx	0.47	0.13	CG12
CS 13 - DEA Perpendicular illuminance Height: 0.020 m	232 lx	141 lx	286 lx	0.61	0.49	CG13


Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 2 - ZONA 1 (LOW))

Calculation objects





The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 2 - ZONA 1 (LOW))

Calculation objects

Calculation surfaces

Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 1 - RP 110kV Perpendicular illuminance Height: 0.020 m	31.5 lx	13.0 lx	44.2 lx	0.41	0.29	CG1
CS 2 - RP 110kV Perpendicular illuminance Height: 0.020 m	43.8 lx	19.7 lx	69.7 lx	0.45	0.28	CG2
CS 3 - RP 110kV Perpendicular illuminance Height: 0.020 m	44.4 lx	24.6 lx	78.2 lx	0.55	0.31	CG3
CS 4 - ETR 2 Perpendicular illuminance Height: 0.020 m	27.5 lx	19.3 lx	33.0 lx	0.70	0.58	CG4
CS 5 - ETR 1 Perpendicular illuminance Height: 0.020 m	27.9 lx	19.4 lx	30.7 lx	0.70	0.63	CG5
CS 6 - Koridor RP Perpendicular illuminance Height: 0.020 m	31.9 lx	15.5 lx	63.5 lx	0.49	0.24	CG6
CS 7 - Ulaz (kapija) Perpendicular illuminance Height: 0.020 m	54.2 lx	31.1 lx	77.9 lx	0.57	0.40	CG7
CS 8 - Ulazni koridor Perpendicular illuminance Height: 0.020 m	17.0 lx	9.00 lx	32.4 lx	0.53	0.28	CG8
CS 9 - Centralni koridor Perpendicular illuminance Height: 0.020 m	30.7 lx	23.9 lx	38.1 lx	0.78	0.63	CG9
CS 10 - Sporedni koridor Perpendicular illuminance Height: 0.020 m	17.7 lx	11.0 lx	31.4 lx	0.62	0.35	CG10
CS 11 - Perimetar 1 Perpendicular illuminance Height: 0.020 m	17.6 lx	9.81 lx	50.8 lx	0.56	0.19	CG11

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 2 - ZONA 1 (LOW))

Calculation objects

CS 12 - Perimetar 2 Perpendicular illuminance Height: 0.020 m	7.24 lx	3.88 lx	20.7 lx	0.54	0.19	CG12
CS 13 - DEA Perpendicular illuminance Height: 0.020 m	232 lx	141 lx	286 lx	0.61	0.49	CG13


Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 1 - ZONA 2 (FULL))

CS 1 - RP 110kV






Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 1 - RP 110kV Perpendicular illuminance Height: 0.020 m	69.4 lx	45.0 lx	78.8 lx	0.65	0.57	CG1

Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))


The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 1 - ZONA 2 (FULL))

CS 2 - RP 110kV








Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 2 - RP 110kV Perpendicular illuminance Height: 0.020 m	80.6 lx	52.4 lx	97.4 lx	0.65	0.54	CG2

Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 1 - ZONA 2 (FULL))

CS 3 - RP 110kV




Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 3 - RP 110kV Perpendicular illuminance Height: 0.020 m	70.4 lx	42.8 lx	93.6 lx	0.61	0.46	CG3

Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 1 - ZONA 2 (FULL))

CS 4 - ETR 2




Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 4 - ETR 2 Perpendicular illuminance Height: 0.020 m	51.6 lx	41.2 lx	70.1 lx	0.80	0.59	CG4

Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 1 - ZONA 2 (FULL))

CS 5 - ETR 1






Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 5 - ETR 1 Perpendicular illuminance Height: 0.020 m	52.6 lx	35.9 lx	71.3 lx	0.68	0.50	CG5

Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 1 - ZONA 2 (FULL))

CS 6 - Koridor RP




Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 6 - Koridor RP Perpendicular illuminance Height: 0.020 m	48.6 lx	20.0 lx	78.2 lx	0.41	0.26	CG6


Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))


The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 1 - ZONA 2 (FULL))

CS 7 - Ulaz (kapija)








Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 7 - Ulaz (kapija) Perpendicular illuminance Height: 0.020 m	54.2 lx	31.1 lx	77.9 lx	0.57	0.40	CG7

Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 1 - ZONA 2 (FULL))

CS 8 - Ulazni koridor




Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 8 - Ulazni koridor Perpendicular illuminance Height: 0.020 m	17.7 lx	9.21 lx	32.4 lx	0.52	0.28	CG8

Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 1 - ZONA 2 (FULL))

CS 9 - Centralni koridor




Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 9 - Centralni koridor Perpendicular illuminance Height: 0.020 m	54.6 lx	33.8 lx	75.0 lx	0.62	0.45	CG9

Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 1 - ZONA 2 (FULL))

CS 10 - Sporedni koridor



Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 10 - Sporedni koridor Perpendicular illuminance Height: 0.020 m	19.3 lx	11.0 lx	37.2 lx	0.57	0.30	CG10

Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 1 - ZONA 2 (FULL))

CS 11 - Perimetar 1




Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 11 - Perimetar 1 Perpendicular illuminance Height: 0.020 m	17.6 lx	9.81 lx	50.8 lx	0.56	0.19	CG11

Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 1 - ZONA 2 (FULL))

CS 12 - Perimetar 2




Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 12 - Perimetar 2 Perpendicular illuminance Height: 0.020 m	9.10 lx	4.32 lx	33.6 lx	0.47	0.13	CG12


Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 1 - ZONA 2 (FULL))

CS 13 - DEA






Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 13 - DEA Perpendicular illuminance Height: 0.020 m	232 lx	141 lx	286 lx	0.61	0.49	CG13

Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 2 - ZONA 1 (LOW))

CS 1 - RP 110kV




Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 1 - RP 110kV Perpendicular illuminance Height: 0.020 m	31.5 lx	13.0 lx	44.2 lx	0.41	0.29	CG1


Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 2 - ZONA 1 (LOW))

CS 2 - RP 110kV






Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 2 - RP 110kV Perpendicular illuminance Height: 0.020 m	43.8 lx	19.7 lx	69.7 lx	0.45	0.28	CG2

Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 2 - ZONA 1 (LOW))

CS 3 - RP 110kV




Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 3 - RP 110kV Perpendicular illuminance Height: 0.020 m	44.4 lx	24.6 lx	78.2 lx	0.55	0.31	CG3

Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 2 - ZONA 1 (LOW))

CS 4 - ETR 2




Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 4 - ETR 2 Perpendicular illuminance Height: 0.020 m	27.5 lx	19.3 lx	33.0 lx	0.70	0.58	CG4

Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 2 - ZONA 1 (LOW))

CS 5 - ETR 1




Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 5 - ETR 1 Perpendicular illuminance Height: 0.020 m	27.9 lx	19.4 lx	30.7 lx	0.70	0.63	CG5

Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 2 - ZONA 1 (LOW))

CS 6 - Koridor RP




Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 6 - Koridor RP Perpendicular illuminance Height: 0.020 m	31.9 lx	15.5 lx	63.5 lx	0.49	0.24	CG6


Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))


The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 2 - ZONA 1 (LOW))

CS 7 - Ulaz (kapija)








Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 7 - Ulaz (kapija) Perpendicular illuminance Height: 0.020 m	54.2 lx	31.1 lx	77.9 lx	0.57	0.40	CG7

Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 2 - ZONA 1 (LOW))

CS 8 - Ulazni koridor




Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 8 - Ulazni koridor Perpendicular illuminance Height: 0.020 m	17.0 lx	9.00 lx	32.4 lx	0.53	0.28	CG8

Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 2 - ZONA 1 (LOW))

CS 9 - Centralni koridor




Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 9 - Centralni koridor Perpendicular illuminance Height: 0.020 m	30.7 lx	23.9 lx	38.1 lx	0.78	0.63	CG9

Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 2 - ZONA 1 (LOW))

CS 10 - Sporedni koridor



Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 10 - Sporedni koridor Perpendicular illuminance Height: 0.020 m	17.7 lx	11.0 lx	31.4 lx	0.62	0.35	CG10

Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 2 - ZONA 1 (LOW))

CS 11 - Perimetar 1




Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 11 - Perimetar 1 Perpendicular illuminance Height: 0.020 m	17.6 lx	9.81 lx	50.8 lx	0.56	0.19	CG11

Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 2 - ZONA 1 (LOW))

CS 12 - Perimetar 2




Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 12 - Perimetar 2 Perpendicular illuminance Height: 0.020 m	7.24 lx	3.88 lx	20.7 lx	0.54	0.19	CG12

Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1 (SCENA 2 - ZONA 1 (LOW))

CS 13 - DEA



100 15000 [lx]


Properties	Ē	E_{min}	E_{max}	U_o (g_1)	g_2	Index
CS 13 - DEA Perpendicular illuminance Height: 0.020 m	232 lx	141 lx	286 lx	0.61	0.49	CG13

Utilisation profile: DIALux presetting (5.1.4 Standard (outdoor transportation area))

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.


Site 1

Control group CG 1



Site 1

Control group CG 2



The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

Site 1

Control groups

Control group	CG 1	CG 2
SCENA 1 - ZONA 2 (FULL)	100	100
SCENA 2 - ZONA 1 (LOW)	–	100

Dimming values [%]

pcs.	Manufacturer	Article No.	Article name	P	Index
4	LUG Light Factory	090380.5L10.021	ATLANTYK 2.0 BASIC LED ED 2900m/840 PC opal IP65 grafit RAL7024	18.0 W	1
12	LUG Light Factory	120212.5L171.41	POWERLUG MINI LED ED 3600lm/740 IP65 as szeroki szary	25.0 W	2
4	LUG Light Factory	120212.5L181.11	POWERLUG MINI LED ED 6350lm/740 IP65 25st. szary	44.0 W	3
7	LUG Light Factory	120212.5L181.31	POWERLUG MINI LED ED 6300lm/740 IP65 as w¹ski szary	44.0 W	4
9	LUG Light Factory	120212.5L181.41	POWERLUG MINI LED ED 6000lm/740 IP65 as szeroki szary	44.0 W	5

The project is not the offer as concerns law. The presented results are approximate and may change. The actual results may vary depending on the conditions in which the luminaires are installed.

OGRADA

POTPORNI ZID

STAZA

KABLOVSKI KANAL

TR2

TR1

POSTROJENJE
35kV

KOMANDNA
ZGRADA

JAMA ZA
ULJE

PROPUST

KAPIJA


-Q1

NE
E
SE
S
SW
W
NW
N

NAPOMENA:

- OVAJ CRTEŽ JE U VLASNIŠTVU PREDUZEĆA CGES I NE SMIJE SE NI U SEGMENTIMA, NI U CJELOSTI REPRODUKOVATI ILI KOPIRATI.
- SVE MJERE PROVJERITI NA LICU MJESTA, A SVAKO ODSTUPANJE OD PROJEKTA PRIJAVITI INVESTITORU. DIMENZIJE SE NE SMIJU SKALIRATI/MIJENJATI.

PROJEKTANT: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD		INVESTITOR: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD	
Objekat: Trafostanica 110/35 kV Ulcinj		Lokacija: Kat. parcela broj 4880, KO Ulcinj, Opština Ulcinj	
Pripremio: Blažo Janković, d.i.e.		Tehnička dokumentacija: Spoljna rasvjeta - TS Ulcinj	Razmjera: R 1:100
Datum izrade: 03.2025. god.		Prilog: Situacija Osnova trafostanice	Broj priloga: 1 / Br. strane: xx



#	Name	Parameter
1	CS 10 – Sporedni koridor	Perpendicular illuminance
2	CS 9 – Centralni koridor	Perpendicular illuminance
3	CS 7 – Ulaz (kapija)	Perpendicular illuminance
4	CS 1 – RP 110kV	Perpendicular illuminance
5	CS 8 – Ulazni koridor	Perpendicular illuminance
6	CS 6 – Koridor RP	Perpendicular illuminance
7	CS 4 – ETR 2	Perpendicular illuminance
8	CS 5 – ETR 1	Perpendicular illuminance
9	CS 2 – RP 110kV	Perpendicular illuminance
10	CS 3 – RP 110kV	Perpendicular illuminance
11	CS 11 – Perimetar 1	Perpendicular illuminance
12	CS 12 – Perimetar 2	Perpendicular illuminance
13	CS 13 – DEA	Perpendicular illuminance


NAPOMENE ZA POLAGANJE KABLOVA U POSTROJENJU:

1. Svi kablovi koji se ne vode kroz kablovske kanale, vode se u zemljanom rovu kroz rebrasto energetsko crijevo Ø50/40mm ili Ø63/50mm na združenim pozicijama naznačenim na crtežu.
2. Svi kablovi za napajanje svjetiljki na portalima postrojenja, vode se nadgradno u SAPA crijevima.
3. Nakon izlaska kablova iz energetskog crijeva iz zemlje, po betonskim stopama portala, kablovi se polažu u regal PNK50 do ormana (RO - A/B/C).
4. Otvore energetskih crijeva treba nakon izvedenih radova zatvoriti kombinovanjem pur-pjene i adekvatnog silikona kako bi se spriječio ulazak vode u iste.
5. Napojni kablovi za ormane RO-A i RO-B se vode u odvojenim crijevima od napojnih kablova za svjetiljke.

NAPOMENA:

- OVAJ CRTEŽ JE U VLASNIŠTVU PREDUZEĆA CGES I NE SMIJE SE NI U SEGMENTIMA, NI U CJELOSTI REPRODUKOVATI ILI KOPIRATI.
- SVE MJERE PROVJERITI NA LICU MJESTA, A SVAKO ODSTUPANJE OD PROJEKTA PRIJAVITI INVESTITORU. DIMENZIJE SE NE SMIJU SKALIRATI/MIJENJATI.

PROJEKTANT: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD		INVESTITOR: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD	
Objekat: Trafostanica 110/35 kV Ulcinj		Lokacija: Kat. parcela broj 4880, KO Ulcinj, Opština Ulcinj	
Pripremio: Blažo Janković, d.i.e.		Tehnička dokumentacija: Spoljna rasvjeta - TS Ulcinj	Razmjera: R 1:100
Datum izrade: 03.2025. god.		Prilog: Situacija Razvod kablova u postrojenju	Broj priloga: 2 / Br. strane: xx



NAPOMENE ZA POLAGANJE KABLOVA UNUTAR OBJEKTA I NA FASADI:

1. Svi kablovi koji se ne vode po PNK regalima, vode se nadgradno kroz HF (halogen-free) cijevi unutar objekta.
2. Za napajanje svjetiljki po fasadi objekta, kablovi se u nakon izlaska iz objekta vode u HF cijevima.
3. Kabl za napajanje rasvjete DEA se polaže u postojećim PVC cijevima do ulaska u DEA "boks", dok se po konstrukciji boksa polaže nadgradno u HF cijevima.
4. Sav potreban materijal za razvod kablova na fasadi (razvodne kutije, spojnice i sl.) mora biti u adekvatnoj IP zaštiti.


NAPOMENA:

- OVAJ CRTEŽ JE U VLASNIŠTVU PREDUZEĆA CGES I NE SMIJE SE NI U SEGMENTIMA, NI U CJELOSTI REPRODUKOVATI ILI KOPIRATI.
- SVE MJERE PROVJERITI NA LICU MJESTA, A SVAKO ODSTUPANJE OD PROJEKTA PRIJAVITI INVESTITORU. DIMENZIJE SE NE SMIJU SKALIRATI/MIJENJATI.

PROJEKTANT: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD		INVESTITOR: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD	
Objekat: Trafostanica 110/35 kV Ulcinj		Lokacija: Kat. parcela broj 4880, KO Ulcinj, Opština Ulcinj	
Pripremio: Blažo Janković, d.i.e.		Tehnička dokumentacija: Spoljna rasvjeta - TS Ulcinj	Razmjera: R 1:100
Datum izrade: 03.2025. god.		Prilog: Objekat TS Rasvjeta na fasadi objekata	Broj priloga: 3 / Br. strane: xx

NAPOMENE ZA POLAGANJE KABLOVA U POSTROJENJU:

1. Svi kablovi koji se ne vode kroz kablovske kanale, vode se u zemljanom rovu kroz rebrasto energetsko crijevo Ø50/40mm ili Ø63/50mm na združenim pozicijama naznačenim na crtežu.
2. Svi kablovi za napajanje svjetiljki na portalima postrojenja, vode se nadgradno u SAPA crijevima.
3. Nakon izlaska kablova iz energetskog crijeva iz zemlje, po betonskim stopama portala, kablovi se polažu u regal PNK50 do ormana (RO - A/B).
4. Otvore energetskih crijeva treba nakon izvedenih radova zatvoriti kombinovanjem pur-pjene i adekvatnog silikona kako bi se spriječio ulazak vode u iste.




NAPOMENA:

- OVAJ CRTEŽ JE U VLASNIŠTVU PREDUZEĆA CGES I NE SMIJE SE NI U SEGMENTIMA, NI U CJELOSTI REPRODUKOVATI ILI KOPIRATI.
- SVE MJERE PROVJERITI NA LICU MJESTA, A SVAKO ODSTUPANJE OD PROJEKTA PRIJAVITI INVESTITORU. DIMENZIJE SE NE SMIJU SKALIRATI/MIJENJATI.

STAZA

PROJEKTANT: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD		INVESTITOR: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD	
Objekat: Trafostanica 110/35 kV Ulcinj		Lokacija: Kat. parcela broj 4880, KO Ulcinj, Opština Ulcinj	
Pripremio: Blažo Janković, d.i.e.		Tehnička dokumentacija: Spoljna rasvjeta - TS Ulcinj	Razmjera: R 1:50
Datum izrade: 03.2025. god.		Prilog: Postrojenje 110kV Rasvjeta na portalima SS (RO-A)	Broj priloga: 4 / Br. strane: xx



NAPOMENE ZA POLAGANJE KABLOVA U POSTROJENJU:

1. Svi kablovi koji se ne vode kroz kablovske kanale, vode se u zemljanom rovu kroz rebrasto energetsko crijevo Ø50/40mm ili Ø63/50mm na združenim pozicijama naznačenim na crtežu.
2. Svi kablovi za napajanje svjetiljki na portalima postrojenja, vode se nadgradno u SAPA crijevima.
3. Nakon izlaska kablova iz energetskog crijeva iz zemlje, po betonskim stopama portala, kablovi se polažu u regal PNK50 do ormana (RO - A/B).
4. Otvore energetskih crijeva treba nakon izvedenih radova zatvoriti kombinovanjem pur-pjene i adekvatnog silikona kako bi se spriječio ulazak vode u iste.

NAPOMENA:

- OVAJ CRTEŽ JE U VLASNIŠTVU PREDUZEĆA CGES I NE SMIJE SE NI U SEGMENTIMA, NI U CJELOSTI REPRODUKOVATI ILI KOPIRATI.
- SVE MJERE PROVJERITI NA LICU MJESTA, A SVAKO ODSTUPANJE OD PROJEKTA PRIJAVITI INVESTITORU. DIMENZIJE SE NE SMIJU SKALIRATI/MIJENJATI.

PROJEKTANT: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD		INVESTITOR: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD	
Objekat: Trafostanica 110/35 kV Ulcinj		Lokacija: Kat. parcela broj 4880, KO Ulcinj, Opština Ulcinj	
Pripremio: Blažo Janković, d.i.e.		Tehnička dokumentacija: Spoljna rasvjeta - TS Ulcinj	Razmjera: R 1:50
Datum izrade: 03.2025. god.		Prilog: Postrojenje 110kV Rasvjeta na portalima SS (RO-A)	Broj priloga: 5 / Br. strane: xx

NAPOMENE ZA POLAGANJE KABLOVA U POSTROJENJU:

1. Svi kablovi koji se ne vode kroz kablovske kanale, vode se u zemljanom rovu kroz rebrasto energetsko crijevo Ø50/40mm ili Ø63/50mm na združenim pozicijama naznačenim na crtežu.
2. Svi kablovi za napajanje svjetiljki na portalima postrojenja, vode se nadgradno u SAPA crijevima.
3. Nakon izlaska kablova iz energetskog crijeva iz zemlje, po betonskim stopama portala, kablovi se polažu u regal PNK50 do ormana (RO - A/B).
4. Otvore energetskih crijeva treba nakon izvedenih radova zatvoriti kombinovanjem pur-pjene i adekvatnog silikona kako bi se spriječio ulazak vode u iste.

S3/9.7m
Z1/B1

S2/9.7m
Z2/B3

S2/9.7m
Z1/B2

S5/9.7m
Z1/B4

S2/9.7m
Z2/B5

S2/9.7m
Z2/B6

S2/9.7m
Z1/B7

RO-B

S2/9.7m
Z2/B8

S2/9.7m
Z1/B9

3 x NYCY 3x1.5mm^2 (B1, B2, B3)
(u zemljanom rovu kroz energetsko crijevo Ø50/40mm)

2 x NYCY 3x1.5mm^2 (B8, B9)
(u zemljanom rovu kroz energetsko crijevo Ø50/40mm)

2 x NYCY 3x1.5mm^2
(u kablovskim kanalima)


KABLOVSKI KANAL

3 x NYCY 3x1.5mm^2
(u kablovskim kanalima)


NAPOMENA:

- OVAJ CRTEŽ JE U VLASNIŠTVU PREDUZEĆA CGES I NE SMIJE SE NI U SEGMENTIMA, NI U CJELOSTI REPRODUKOVATI ILI KOPIRATI.
- SVE MJERE PROVJERITI NA LICU MJESTA, A SVAKO ODSTUPANJE OD PROJEKTA PRIJAVITI INVESTITORU. DIMENZIJE SE NE SMIJU SKALIRATI/MIJENJATI.

PROJEKTANT: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD		INVESTITOR: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD	
Objekat: Trafostanica 110/35 kV Ulcinj		Lokacija: Kat. parcela broj 4880, KO Ulcinj, Opština Ulcinj	
Pripremio: Blažo Janković, d.i.e.		Tehnička dokumentacija: Spoljna rasvjeta - TS Ulcinj	Razmjera: R 1:50
Datum izrade: 03.2025. god.		Prilog: Postrojenje 110kV Rasvjeta na portalima (RO-B)	Broj priloga: 6 / Br. strane: xx



PROJEKTANT: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD		INVESTITOR: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD	
Objekat: Trafostanica 110/35 kV Ulcinj		Lokacija: Kat. parcela broj 4880, KO Ulcinj, Opština Ulcinj	
Pripremio: Blažo Janković, d.i.e.		Tehnička dokumentacija: Spoljna rasvjeta - TS Ulcinj	Razmjera: R 1:50
Datum izrade: 03.2025. god.		Prilog: Postrojenje 110kV Rasvjeta na zidu ETR-a	Broj priloga: 7 / Br. strane: xx



NAPOMENE ZA POLAGANJE KABLOVA ZA RASVJETU DEA:

1. Svi kablovi koji se ne vode po PNK regalima, vode se nadgradno kroz HF (halogen-free) cijevi unutar objekta.
2. Kabl za napajanje rasvjete DEA se polaže u postojećim PVC cijevima do ulaska u DEA "boks", dok se po konstrukciji boksa polaže nadgradno u HF cijevima.

NAPOMENA:

- OVAJ CRTEŽ JE U VLASNIŠTVU PREDUZEĆA CGES I NE SMIJE SE NI U SEGMENTIMA, NI U CJELOSTI REPRODUKOVATI ILI KOPIRATI.
- SVE MJERE PROVJERITI NA LICU MJESTA, A SVAKO ODSTUPANJE OD PROJEKTA PRIJAVITI INVESTITORU. DIMENZIJE SE NE SMIJU SKALIRATI/MIJENJATI.

PROJEKTANT: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD		INVESTITOR: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD	
Objekat: Trafostanica 110/35 kV Ulcinj		Lokacija: Kat. parcela broj 4880, KO Ulcinj, Opština Ulcinj	
Pripremio: Blažo Janković, d.i.e.		Tehnička dokumentacija: Spoljna rasvjeta - TS Ulcinj	Razmjera: R 1:50
Datum izrade: 03.2025. god.		Prilog: Objekat TS Rasvjeta DEA	Broj priloga: 8 / Br. strane: xx

Upravljanje/kontrola zone 1
Upravljanje/kontrola zone 2

	RO-A		RO-B		S3+S5	2xS5	S4		2xS5	2xS2	3xS5		2xS5		4xS1		UKUPNO PO FAZI: Z1	UKUPNO PO FAZI: Z1 + Z2	UKUPNO:
L3	132 W		176 W		69 W						75 W						276W	452 W	
L2	132 W		88 W			50 W			50 W	88 W							276 W	408 W	1 252 W
L1	113 W		113 W				44 W						50 W		72 W		270 W	392 W	

RO-A
L1 L2 L3
NYCY 4x4mm²
RO-B
L1 L2 L3
NYCY 4x4mm²
S3+S5
NYCY 3x1,5mm²
2xS5
NYCY 3x1,5mm²
S4
NYCY 3x1,5mm²
2xS5
NYCY 3x1,5mm²
2xS2
NYCY 3x1,5mm²
3xS5
NYCY 3x1,5mm²
2xS5
NYCY 3x1,5mm²
4xS1
NYCY 3x1,5mm²
Foto-ćelija na fasadi objekta
FOTO
NYCY 5x1,5mm² na/sa KO
NYCY 3x1,5mm² na/sa KO

na vratima ormana **
L1 L2 L3
C6A C6A C6A
KZ2-A
KZ1-A
L1 L2 L3
D20A
KZ2-B
KZ1-B
L1 L2 L3
D20A
C10A C10A C10A
KZ1-F1
C10A C10A C10A
KZ1-F2
C10A
KZ2-F3
C10A
KZ1-DEA
Z1 Z2
na vratima ormana*
C6A C6A
L1 L2 L3 RO-A RO-B 1 2 3 4 5 7 6 8 K1(SR) K2(DEA)

GOSR

ISFT 160/80A
V50-3+NPE-280
OBO-Bettermann
ISFT 160/40A

H07V-K 1x35 mm²
sa uzemljivačkog provodnika

Pi = 1.252W
k = 1,0
Pj = 1.252 W

NYCY 4x6 mm²
sa NN razvoda

ISFT 160/25A
NN

NAPOMENE:

* - Signalne sijalice 220V u crvenoj boji na vratima ormana, za signalizaciju aktivnosti zona spoljne rasvjete (Z1 i Z2). Natpis iznad sijalica "komanda Z1" i " komanda Z2".

** - Signalne sijalice 220V u zelenoj boji na vratima ormana, za signalizaciju prisustva faza. Natpis iznad sijalica "L1", "L2" i "L3" .


U ormanu ostaviti minimum 30% slobodnog prostora.

PROJEKTANT: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD		INVESTITOR: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD	
Objekat:	Trafostanica 110/35 kV Ulcinj	Lokacija:	Kat. parcela broj 4880, KO Ulcinj, Opština Ulcinj
Pripremio:	Blažo Janković, d.i.e.	Tehnička dokumentacija: Spoljna rasvjeta - TS Ulcinj	Razmjera: - // -
Datum izrade: 03.2025. god.		Prilog: Jednopolna šema ormana GOSR	Broj priloga: 9 / Br. strane: xx

Upravljanje/kontrola zone 1

Upravljanje/kontrola zone 2

L3		44 W				44 W			44 W			132 W
L2				44 W	44 W		44 W					132 W
L1	44 W		25 W					44 W				113 W
											UKUPNO PO FAZI:	UKUPNO: 377 W




Pi = 377 W
k = 1,0
Pj = 377 W

PROJEKTANT: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD		INVESTITOR: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD	
Objekat: Trafostanica 110/35 kV Ulcinj		Lokacija: Kat. parcela broj 4880, KO Ulcinj, Opština Ulcinj	
Pripremio: Blažo Janković, d.i.e.		Tehnička dokumentacija: Spoljna rasvjeta - TS Ulcinj	Razmjera: - // -
Datum izrade: 03.2025. god.		Prilog: Jednopolna šema ormana RO-A	Broj priloga: 10 / Br. strane: xx

Upravljanje/kontrola zone 1


Upravljanje/kontrola zone 2



Pi = 377 W
k = 1,0
Pj = 377 W

PROJEKTANT: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD	INVESTITOR: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD
Objekat: Trafostanica 110/35 kV Ulcinj	Lokacija: Kat. parcela broj 4880, KO Ulcinj, Opština Ulcinj
Pripremio: Blažo Janković, d.i.e.	Tehnička dokumentacija: Spoljna rasvjeta - TS Ulcinj; Razmjera: - // -
Datum izrade: 03.2025. god.	Prilog: Jednopolna šema ormana RO-B; Broj priloga: 11; Br. strane: xx


Upravljanje/kontrola zone 1
Upravljanje/kontrola zone 2



NAPOMENE:

* - Grebenaste sklopke na vratima ormana, za komandu aktivnosti zona spoljne rasvjete (Z1 i Z2).
Natpis iznad sijalica "komanda Z1" i " komanda Z2".
** - Signalne sijalice 220V na vratima ormana, za signalizaciju dovodnih i odvodnih signala:
Z1-D - Signalizacija dovoda signala Z1, zelene boje. Natpis "DOVOD Z1"
Z2-D - Signalizacija dovoda signala Z2, zelene boje. Natpis "DOVOD Z2 "
Z1-A - Signalizacija aktivacije signala Z1 - automatski režim, crvene boje. Natpis " Z1 AUTO "
Z1-R - Signalizacija aktivacije signala Z1 - ručni režim, crvene boje. Natpis " Z1 RUČNO "
Z2-O - Signalizacija aktivacije signala Z2, crvene boje. Natpis " Z2 UKLJUČENO "
D-D - Signalizacija dovoda signala DEA, zelene boje. Natpis " DOVOD DEA "
D-O - Signalizacija aktivacije signala DEA, crvene boje. Natpis " DEA UKLJUČENO "

PROJEKTANT: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD		INVESTITOR: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD	
Objekat: Trafostanica 110/35 kV Ulcinj		Lokacija: Kat. parcela broj 4880, KO Ulcinj, Opština Ulcinj	
Pripremio: Blažo Janković, d.i.e.		Tehnička dokumentacija: Spoljna rasvjeta - TS Ulcinj	Razmjera: - // -
Datum izrade: 03.2025. god.		Prilog: Jednopolna šema ormana KO	Broj priloga: 12 / Br. strane: xx



GOSR - Glavni orman spoljne rasvjete

RO-A - Razvodni orman - stub A

RO-B - Razvodni orman - stub B

NYCY 4x4mm2


NYCY 3x1.5mm2

PROJEKTANT: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD		INVESTITOR: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD	
Objekat: Trafostanica 110/35 kV Ulcinj		Lokacija: Kat. parcela broj 4880, KO Ulcinj, Opština Ulcinj	
Pripremio: Blažo Janković, d.i.e.		Tehnička dokumentacija: Spoljna rasvjeta - TS Ulcinj	Razmjera: - // -
Datum izrade: 03.2025. god.		Prilog: Blok šema napajanja SR	Broj priloga: 13 / Br. strane: xx

LEGENDA OPREME NA CRTEŽIMA			količina
S1		Linijska svjetiljka 18W, difuzne emisije svijetla, opalnog difuzora, 2900lm, CRI80, 4000K, IP65 IK08, 230Vac, slična tipu 090380.5L10.021 ATLANTYK 2.0 BASIC, LUG Poljska.	4
S2		Reflektorska svjetiljka 44W, široko-asimetričnog snopa optike ASW, 6000lm, CRI70, 4000K, IP65 IK09, 230Vac, slična tipu 120212.5L181.41 POWERLUG MINI, LUG Poljska.	9
S3		Reflektorska svjetiljka 44W, usko-asimetričnog snopa optike ASN, 6300lm, CRI70, 4000K, IP65 IK09, 230Vac, slična tipu 120212.5L181.31 POWERLUG MINI, LUG Poljska.	7
S4		Reflektorska svjetiljka 44W, uskog snopa optike 25 stepeni, 6350lm, CRI70, 4000K, IP65 IK09, 230Vac, slična tipu 120212.5L181.11 POWERLUG MINI, LUG Poljska.	4
S5		Reflektorska svjetiljka 25W, široko-asimetričnog snopa optike ASW, 3600lm, CRI70, 4000K, IP65 IK09, 230Vac, slična tipu 120212.5L171.41 POWERLUG MINI, LUG Poljska.	12
FĆ	FOTO	Foto-ćelija za paljenje/gašenje SR . Vanjska montaža za ugradnju na zid, minimalna zaštita IP44.	1
		Razvodni orman	3

LEGENDA OZNAKE ELEMENATA U TABLI GOSR	
KZ1-A	Kontaktor 2NO 25A - zona 1 - RO-A
KZ2-A	Kontaktor 1NO 25A - zona 2 - RO-A
KZ1-B	Kontaktor 2NO 25A - zona 1 - RO-B
KZ2-B	Kontaktor 1NO 25A - zona 2 - RO-B
KZ1-F1	Kontaktor 3NO 25A - zona Z1 - Fasada objekta 1
KZ1-F2	Kontaktor 3NO 25A - zona Z1 - Fasada objekta 1
KZ2-F3	Kontaktor 1NO 25A - zona Z2 - Zid ETR
K-DEA	Kontaktor 1NO 25A - DEA - prostor agregata
GS 1-0	Grebenasta sklopka/prekidač na vratima ormana 1-0, 1P, 20A, 230V
GS 1-0-2	Grebenasta sklopka/izbornik položaja na vratima ormana 1-0-2, 1P, 20A, 230V
⊗	Signalna sijalica 220V
FĆ	Foto-ćelija na fasadi objekta.
	Upravljanje/kontrola zone 1
	Upravljanje/kontrola zone 2


LEGENDA OZNAKE SVJETILJKI



NAPOMENA:

- OVAJ CRTEŽ JE U VLASNIŠTVU PREDUZEĆA MONCORE DOO I NE SMIJE SE NI U SEGMENTIMA, NI U CJELOSTI REPRODUKOVATI ILI KOPIRATI.
- SVE MJERE PROVJERITI NA LICU MJESTA, A SVAKO ODSTUPANJE OD PROJEKTA PRIJAVITI PROJEKTANTU. DIMENZIJE SE NE SMIJU SKALIRATI/MIJENJATI.

PROJEKTANT: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD		INVESTITOR: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD	
Objekat: Trafostanica 110/35 kV Ulcinj		Lokacija: Kat. parcela broj 4880, KO Ulcinj, Opština Ulcinj	
Pripremio: Blažo Janković, d.i.e.		Tehnička dokumentacija: Spoljna rasvjeta - TS Ulcinj	Razmjera: - // -
Datum izrade: 10.2024. god.		Prilog: Legenda opreme	Broj priloga: 14 / Br. strane: xx



#	Name	Parameter
1	CS 10 – Sporedni koridor	Perpendicular illuminance
2	CS 9 – Centralni koridor	Perpendicular illuminance
3	CS 7 – Ulaz (kapija)	Perpendicular illuminance
4	CS 1 – RP 110kV	Perpendicular illuminance
5	CS 8 – Ulazni koridor	Perpendicular illuminance
6	CS 6 – Koridor RP	Perpendicular illuminance
7	CS 4 – ETR 2	Perpendicular illuminance
8	CS 5 – ETR 1	Perpendicular illuminance
9	CS 2 – RP 110kV	Perpendicular illuminance
10	CS 3 – RP 110kV	Perpendicular illuminance
11	CS 11 – Perimetar 1	Perpendicular illuminance
12	CS 12 – Perimetar 2	Perpendicular illuminance
13	CS 13 – DEA	Perpendicular illuminance

Luminaire list (TS ULCINJ)

Index	Symbol	Manufacturer	Article name	Item number	Fitting	Luminous flux	Maintenance factor	Connected load	Quantity
S1		LUG Light Factory	ATLANTYK 2.0 BASIC LED ED 2900lm/840 PC opal IP65	090380.5L10.021	1x LED-4000K	2900 lm	0.90	18 W	4
S2		LUG Light Factory	POWERLUG MINI LED 6000lm/740 IP65 AS szeroki szary	120212.5L181.41	1x LED 4000K	6000 lm	0.90	44 W	9
S3		LUG Light Factory	POWERLUG MINI LED 6300lm/740 IP65 AS wyski szary	120212.5L181.31	1x LED 4000K	6300 lm	0.90	44 W	7
S4		LUG Light Factory	POWERLUG MINI LED 6350lm/740 IP65 25 st. szary	120212.5L181.11	1x LED 4000K	6350 lm	0.90	44 W	4
S5		LUG Light Factory	POWERLUG MINI LED 3600lm/740 IP65 AS szeroki szary	120212.5L171.41	1x LED 4000K	3600 lm	0.90	25 W	12

NAPOMENE ZA PRIPREMU FOTOMETRIJSKIH PRORAČUNA:

1. Sve kalkulacijske površine se postavljaju na 0.02m visine.
2. Svi objekti ucrtani na crtežu moraju biti tretirani i u proračunu, sa njihovim visinama naznačenim na crtežu.
3. "Maintenance factor" svjetiljki može biti maksimalno 0.9.
4. Mrežu kalkulacijskih tačaka na površinama prilagoditi tačkama prikazanim na crtežu.
5. Za kalkulacijske površine perimetralnih zona, maksimalna udaljenost tačaka (grid) je 0,6m x 0,6m.
6. Za kalkulacijske površine ulazne kapije maksimalna udaljenost tačaka (grid) je 0.8m x 0.8m.
6. Za kalkulacijske površine svih koridora maksimalna udaljenost tačaka (grid) je 1m x 1m.
7. Za kalkulacijske površine u postrojenjima i transformatorima, maksimalna udaljenost tačaka (grid) je 0,8m x 1m (gledano po užoj strani).
8. Na portalima u 110kV postrojenju svjetiljke predvidjeti na maksimalno 9.7m odnosno 6.7m (zavisno od visine portala).
9. Na pregradnom zidu transformatora visina montaže svjetiljki je 5.0m.
10. Na fasadi objekta 35kV postrojenja visina montaže svjetiljki je 9.2m, dok je na komandnom objektu visina montaže svjetiljki 7.8m.
11. Za prostor DEA, pozicije i visine montaže svjetiljki su fiksne zbog uslova na licu mjesta.
12. Refleksije podnih površina maksimalno 20%.
13. Refleksije zidova objekata maksimalno 50%.
14. Zbog uticaja stubova portala u postrojenjima, iste je potrebno tretirati u proračunu. Zbog njihove rešetkaste prirode i uticaja na distribuciju svjetla, iste formirati kao "prozirne" (transparent) sa refleksijom ne većom od 50% (reflection factor) i propustom ne većim od 40% (degree of transmission).

NIVOI OSVIJETLJENOSTI PO ZONAMA:

Komplet rasvjetu postrojenja treba dizajnirati na način da postoje dva nivoa osvjetljaja, tj dvije zone paljenja. Svjetiljke na fasadi moraju pokriti sve strane objekta i biti uključene u zoni 1, dok DEA zona se tretira kao nezavisna zona paljenja i pozicije svjetiljki su fiksne.

Zona 1, osnovni nivo ima sledeće potrebe u pogledu srednjeg nivoa osvjetljaja i ravnomjernosti:
Ulazna kapija - Em > 50lx i Uo > 0.5
Ulazni, Centralni i Sporedni koridor - Em > 15lx i Uo > 0.5
Koridor RP 110kV - Em > 30lx i Uo > 0.4
Postrojenja 110kV i ETR - Em > 25lx i Uo > 0.4
Perimetri - Em > 5lx i Uo >0.5

Zona 2, maksimalni nivo ima sledeće potrebe u pogledu srednjeg nivoa osvjetljaja i ravnomjernosti:
Ulazna kapija - Em > 50lx i Uo > 0.5
Ulazni, Centralni i Sporedni koridor - Em > 15lx i Uo > 0.5
Koridor RP 110kV - Em > 40lx i Uo > 0.4
Postrojenja 110kV i ETR - Em > 50lx i Uo > 0.6
Perimetri - Em > 7.5lx i Uo >0.4

Nezavisna zona (paljenje):
DEA prostor - EM > 200lx i Uo > 0.6

NAPOMENA:

- OVAJ CRTEŽ JE U VLASNIŠTVU PREDUZEĆA CGES I NE SMIJE SE NI U SEGMENTIMA, NI U CJELOSTI REPRODUKOVATI ILI KOPIRATI.
- SVE MJERE PROVJERITI NA LICU MJESTA, A SVAKO ODSTUPANJE OD PROJEKTA PRIJAVITI INVESTITORU. DIMENZIJE SE NE SMIJU SKALIRATI/MIJENJATI.

PROJEKTANT: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD		INVESTITOR: CRNOGORSKI ELEKTROPRENOSNI SISTEM AD	
Objekat: Trafostanica 110/35 kV Ulcinj		Lokacija: Kat. parcela broj 4880, KO Ulcinj, Opština Ulcinj	
Pripremio: Blažo Janković, d.i.e.		Tehnička dokumentacija: Spoljna rasvjeta - TS Ulcinj	Razmjera: R 1:100
Datum izrade: 03.2025. god.		Prilog: Situacija Podloga za fotometrijski proračun	Broj priloga: 15 / Br. strane: xx